




Ahuja offers an elegant & rugged six channel audio mixer **AMX-60**. This compact mixer has all the basic ingredients of a professional mixer like electronically balanced MIC/LINE inputs, two band equalisation, five point output level display, clip indicators, higher overload margins etc. Ideal for use in Houses of Worship, Educational Institutions, DJs and a variety of PA Applications.

### Features

- Six channel professional PA mixer which is light-weight and easily portable.
- Compact, robust & aesthetically superior housing in silver coloured finish.
- Upto six low impedance Microphones can be connected in either balanced or unbalanced configuration, through a 1/4" stereo jack socket.
- Alternatively, each channel input can accept a balanced or an unbalanced line source like CD Player, Keyboard, Guitar Pre-amp., Drum Kit etc.
- Each channel has a push switch for selecting between MIC and LINE input.
- GAIN Control on each channel for optimum adjustment of the input sensitivities.
- Active BASS & TREBLE circuitry in each channel for desired equalisation of the input signal.
- Each channel has a CLIP LED which glows when the level of input signal is excessive and the same should be reduced by the gain control.
- PAN control on each channel for desired distribution of the signal to left and right outputs.
- LINE level L & R outputs through 1/4" jack sockets.
- Individual 5-segment LED array indication for accurate setting of L&R line output levels.
- Individual MASTER volume controls for left & right line outputs.
- Option of MONO/STEREO mode of operation through a push switch.
- Power ON indication through a blue LED.
- Operates on 220 - 240V, 50Hz AC Mains.



- ✓ Live PA
- ✓ DJ Mixing
- ✓ Sub-Mixing

## Specifications

MIC INPUT	
(Impedance/Gain)	: 2k $\Omega$ Balanced/62 dB
	1k $\Omega$ Unbalanced/62dB
LINE INPUT	
(Impedance/Gain)	: 20k $\Omega$ Balanced/42dB
	10k $\Omega$ Unbalanced/42dB
THD	: < 0.1 %
FREQUENCY RESPONSE	: 20Hz-18 kHz (-1dB)
EQUALISATION	
Bass/Treble	: $\pm 12$ dB at 100 Hz / $\pm 12$ dB at 10kHz
LINE OUTPUT L/R	
Nominal	: 0dBm (775mv)
Maximum	: +18dBm (6.5V)
OUTPUT IMPEDANCE	: 600 $\Omega$
S/N RATIO	: > 68dB
CLIP LED INDICATION	: 4dB prior to true clip
POWER SUPPLY	: 220-240V AC 50Hz
DIMENSIONS	: W295 X H70 X D180mm
WEIGHT	: 2.4 Kg

Design and Specifications are subject to change without notice. • **AHUJA** is a registered trademark of Ahuja Radios in India and other countries.  
 © Copyright Ahuja Radios, 2008. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law.  
 No part of the compilation may be reproduced in any manner or translated without written permission.

0011/08

**TRUSOUND PVT. LTD.** • C-89, Sector IV, Noida, Gautam Budh Nagar-201 301 (UP)

Regd. Office : 125E, Okhla Industrial Estate, New Delhi-110 020

Tel.: +91-120-2551452/53 Fax : +91-120-2553677

E-mail: [ahuja@ahujaradios.com](mailto:ahuja@ahujaradios.com) Website: [www.ahujaradios.com](http://www.ahujaradios.com)