



Introducing a new 5 Channel Mixer Pre-amplifier in which each input channel has switchable sensitivity: nominally 0.6mV (for wired microphones), 50 mV (for wireless microphones), and 100mV (for other Aux sources like CD etc). This will enable the mixer to give ideal sound quality with any of these various input sources. The selectable sensitivity will enable customers to use up-to 5 wireless microphones, without the unwanted distortion which comes due to sensitivity mismatch with the amplifier.

## FEATURES

- 5 Mic/5 Auxiliary inputs with Selectable Sensitivity.
- Separate volume control for each Mic/Aux input.
- Separate master control for adjusting mixed output level.
- Peak LED for setting optimum distortion-free output levels.
- AC Mains & 12V Car Battery Operation.

## SPECIFICATIONS

Frequency Response	20Hz-20,000Hz $\pm$ 3dB
Input Channels	5 $\times$ Mic 0.6mV/4.7k $\Omega$ or 5 $\times$ Aux HI 100mV/470k $\Omega$ or 5 Aux LO 50mV/470k $\Omega$ (selectable)
Output	200mV/600 $\Omega$
Distortion	<1%
S/N Ratio	Better than 40dB
Power Supply	AC - 240V 50Hz DC - 12V Car Battery
Dimensions	W220 $\times$ H60 $\times$ D120 mm
Weight	1.25kg

*Specifications claimed are subject to permissible production tolerances.*

Design and Specifications are subject to change without notice. • AHUJA is a registered trademark of Ahuja Radios in India and other countries.  
© Copyright Ahuja Radios, 2008. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law.  
No part of the compilation may be reproduced in any manner or translated without written permission.