

AHUJA®

DPA-370

PA Amplifier + Digital Player



DPA-370 is PA Amplifier with inbuilt Mp3 Digital Player. Built with a aesthetically designed plastic front panel, it is an elegant, state-of-the-art product.

The Digital Player plays back clear, high quality Mp3 music from an USB drive. A remote control is provided for easily operating the Digital Player from a distance. This, combined with 2 microphone inputs, 1 Aux input and provision for multiple speaker connection makes this product ideally suitable for a variety of music programmes and public address application.

- 2 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Line Output for connecting to a Booster Amplifier.
- Tone for cutting excessive high frequencies.
- Instant transfer to DC Power (Car Battery) if AC power fails.
- Monitor LED for output monitoring

Specifications

POWER OUTPUT	35W Max., 28W RMS at 10% THD, 25W RMS at 5% THD
INPUT CHANNELS	2 × Mic. 0.5mV/2.5kΩ, 1 × Aux 50mV/330kΩ
FREQUENCY RESPONSE	100-12,000Hz ±3dB
SIGNAL TO NOISE RATIO	58dB
TONE CONTROLS	Tone: -10dB at 10kHz
LINE OUTPUTS	250mV/3.5kΩ
SPEAKER OUTPUTS	4Ω, 8Ω, 16Ω & 100V
DIGITAL PLAYER	MP3 Player with USB reader
POWER SUPPLY	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery
DIMENSIONS	W230 × H95 × D260 mm
WEIGHT	4.5kg

Design and Specifications are subject to change without notice. AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2010. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of the compilation may be reproduced in any manner or translated without written permission.

TRUSOUND PVT. LTD. C-89, Sector IV, Noida, Gautam Budh Nagar-201 301 (UP)
Regd. Office : 125E, Okhla Industrial Estate, New Delhi-110 020
Tel.: +91-120-4665665 Fax : +91-120-4665621 E-mail: trusoundsupport@airtelmail.in

00/07/10