



DPA-570

PA Amplifier + Digital Player



DPA-570 is a PA amplifier with an inbuilt MP3 Digital Player, making it a versatile multi-application music center. The Digital Player accepts USB drives, and reproduces clear, high quality music. A remote control is provided for controlling the functions of the Digital Player from a distance. This, combined with 3 microphone inputs, 1 Aux input, and provision for multiple speaker connections makes this ideally suitable for a variety of music programmes and public address applications.

- 3 Mic & 1 Aux Input.
- Built-in MP3 player with USB reader and remote control.
- Line Output for connecting to a Booster Amplifier.
- Active Bass & Treble controls.
- Instant transfer to DC Power (Car Battery) if AC power fails.
- Monitor LED for output monitoring

Specifications

POWER OUTPUT	75W Max., 50W RMS at 10% THD, 45W RMS at 5% THD
INPUT CHANNELS	3 × Mic. 0.6mV/4.7kΩ, 1 × Aux 100mV/330kΩ
FREQUENCY RESPONSE	50-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	55dB
TONE CONTROLS	Bass: ±10dB at 100Hz Treble: ±10dB at 10kHz
OUTPUTS	Line: 400mV/3.5kΩ
SPEAKER OUTPUTS	4Ω, 8Ω, 16Ω & 100V
DIGITAL PLAYER	MP3 Player with USB reader
POWER SUPPLY	AC: 220-240V 50/60Hz, DC: 12-14V Car Battery
DIMENSIONS	W305 × H120 × D305 mm
WEIGHT	7.0kg

Design and Specifications are subject to change without notice. AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2009. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of the compilation may be reproduced in any manner or translated without written permission.

TRUSOUND PVT. LTD. C-89, Sector IV, Noida, Gautam Budh Nagar-201 301 (UP)
Regd. Office : 125E, Okhla Industrial Estate, New Delhi-110 020
Tel.: +91-120-4665665 Fax : +91-120-4665621 E-mail: trusoundsupport@airtelmail.in

0013/09