

Deadly
Dynamic
Durable

DJ Amplifier + Digital Player

UBA-500DP


- ✓ MP3 Digital Player
- ✓ Cut Boost type Bass & Treble Controls
- ✓ Microphone and AUX Input
- ✓ Mains OVER-VOLTAGE & Thermal Protection Circuits



POWER PACKED PUNCH

ABSOLUTE VALUE FOR MONEY !

UBA-500DP DJ Amplifier + Digital Player



- Designed for use in a wide variety of PA applications and DJ performances.
- UBA-500DP is a 500 Watts amplifier which can be connected to various input sources like a Microphone, PA Mixer, DJ Mixer, CD Player, Cassette Player, Keyboard etc.
- The amplifier has cut and boost type tone controls which provides precise and accurate tonal setting of the programme.
- Line Input and Line Output have been provided to enable interconnections with other power amplifiers.
- Built-in Mp3 Digital Player with remote control.
- Circuit Protector Device has been provided which safeguards the amplifier against overload and short circuit.
- The amplifier has built-in protection against over voltage in AC mains supply while operating on a Genset.
- Indicator LEDs for Power, Signal, Temp, Overload and Fault conditions have been provided.
- Ease of operation, combined with service accessibility has been optimized in the design.
- 2Ω speaker matching provided in addition to 4Ω & 8Ω

Power Output	650W RMS Max. 500W RMS at 10%THD 475W RMS at 5% THD 450W RMS at 2% THD
Output Regulation	≤ 2dB no load to full load at 1kHz
Input Channels	1 × Mic 1mV / 4.7kΩ (Mic source impedance 50Ω to 1kΩ) 1 × Aux 100mV / 470kΩ 1 × Aux 250mV / 20kΩ 1 × CD 250mV / 20kΩ Line Input 1V / 10kΩ
Digital Player	Mp3 Player with Remote Control (USB, SD and MMC card reader)
Frequency Response	50Hz–18,000Hz ±3dB
Signal to Noise Ratio	60dB
Tone Controls	Bass (100Hz) : ± 8dB Treble (10kHz): ±8dB
Line Output	1V/1kΩ
Output Taps for Speaker Matching	2Ω, 4Ω & 8Ω
Power Supply	AC: 220-240V 50/60Hz
Protections	2 × 20 Amp fuse in ± DC supply 5 Amp circuit breaker in AC mains Protected against high AC mains voltage, overload and temperature
AC Power Consumption	1000 VA
Dimensions	W482 × H166 × D435 mm
Weight	23.5kg

AHUJA is a registered trademark of Ahuja Radios in India and other countries. © Copyright Ahuja Radios, 2010. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law. No part of the compilation may be reproduced in any manner or translated without written permission.

TRUSOUND PVT. LTD.

C-89, Sector IV, Noida, Gautam Budh Nagar-201 301 (UP)
Regd. Office : 125E, Okhla Industrial Estate, New Delhi-110 020
Tel.: +91-120-4665665 Fax : +91-120-4665621 E-mail: trusoundsupport@airtelmail.in