

Low Power PA Amplifier



UTR-40

30 WATTS ■ AC, 12V DC & Dry Cells Operation

- 3 Mic & 1 Aux Input.
- Cut type Bass & Treble controls.
- 3 POWER SOURCE Amplifier: AC mains, 12V DC (Car Battery) and 12V DC Dry Cell (Two Banks of 8×1.5V Um-1 cell each).
- Extremely portable and ideal for use in remote places without electricity.
- Low current consumption for long battery life.

SPECIFICATIONS	UTR-40
Power OUTPUT	45W Max., 30W RMS at 10% THD
INPUT CHANNELS	3 × Mic 0.65mV/4.7kΩ, 1 × Aux 100mV/470kΩ
FREQUENCY RESPONSE	100-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass: -10dB at 100Hz Treble: -10dB at 10kHz
SPEAKER OUTPUTS	4Ω, 8Ω, 16Ω & 100V
POWER SUPPLY	AC: 220-240V 50/60Hz DC: 12V (Car Battery) DC: 12V (Dry Cells 8 × UM-1) Two Banks
POWER CONSUMPTION	AC: 90VA DC: 1.8A
DIMENSIONS	W280 × H115 × D270 mm
WEIGHT	5.3kg