



SSA-250DP is a PA mixer amplifier of rated output 250 watts, fitted with a MP3 Digital Player. The Digital Player features outstanding wide spectrum sound quality, combined with highly useful features like LCD display, remote control, and facilities for REPEAT, PAUSE, VOLUME UP / DOWN etc. It can read USB drives, SD & MMC cards.


SSA-250DP has all the other features of the popular SSA-250M model, like 6 Mic inputs, 2 Aux inputs, cut / boost type bass & treble controls, resettable circuit protector, and provision for connecting 24V battery. Facility is given for mixing MP3 playback signal with both Aux and most mic inputs.

This is a rugged and highly reliable product, ideally suited for a wide variety of music and public address applications.

Features

- 6 Mic & 2 Aux Inputs.
- Built-in MP3 player with LCD display, remote control, for USB, SD/MMC cards.
- Preamplifier and Line Output for connecting to a Booster Amplifier and for recording the programme.
- Line Input for connecting the output from any external mixer or permitting SSA-250DP to be used as a Booster Power Amplifier.
- Resettable circuit breaker for protection against overload and short circuit.
- Instant transfer to DC power (2 × 12C Car Battery) if AC power fails.
- Box Speaker/Driver Unit selector switch. Bass boost defeated at Driver Unit position for safer operation of driver units.

Rear Panel



Specifications

SPECIFICATIONS

POWER OUTPUT	300W Max., 250W RMS at 10% THD 220W RMS at 5% THD, 200W RMS at 2% THD
OUTPUT REGULATION	≤ 2 dB, no load to full load at 1kHz
INPUT CHANNELS	6 × Mic 0.65mV/4.7kΩ, 2 × Aux 100mV/470 kΩ 1 × Line 1V/50kΩ
FREQUENCY RESPONSE	50-15,000Hz ±3dB
SIGNAL TO NOISE RATIO	60dB
TONE CONTROLS	Bass: ±10dB at 100Hz, Treble: ±10dB at 10kHz
OUTPUT	Preamp 200mV/600W, Line 1V/1kΩ
SPEAKER OUTPUT	4Ω, 8Ω, 70V & 100V
DIGITAL PLAYER	MP3 Player with USB, SD and MMC Card Reader
POWER SUPPLY	AC: 220-240V 50/60Hz DC: 24V (2×12V Car Battery)
POWER CONSUMPTION	AC: 500VA DC: 6A
DIMENSIONS	W450 × H160 × D340 mm
WEIGHT	16.0kg

Design and Specifications are subject to change without notice. AHUJA is a registered trademark of Ahuja Radios in India and other countries.
© Copyright Ahuja Radios, 2012. All rights reserved. Any unauthorized reproduction or use of logos, images or design elements is strictly prohibited by law.
No part of the compilation may be reproduced in any manner or translated without written permission.

AHUJA RADIOS

215, Okhla Industrial Estate, New Delhi-110020, INDIA
Tel.: +91-11-26831549, 41612474 Fax: +91-11-26847287 E-mail: ahuja@ahujaradios.com
Website: www.ahujaradios.com