

BASIC SERIES

The Basic Series from Studiomaster Professional are a range of high quality compact mixers designed with features suitable for both beginners as well professionals.



Models Available:

Basic Cub S: Standard 5 Channel mixer

Basic Cub : 5 Channel mixer + Delay EFX

Basic Cub U: 5 Channel mixer + Delay EFX + USB

- 5 channel mixer (4 Mono, 1 Stereo Input).
- Balanced 1/4" phono jack for Mic/Line Inputs.
- Gain control with 2 band EQ per channel.
- ¼" TRS Jack unbalanced L/R Main Output.
- USB MP 3 Player on Basic Cub U plays & display track numbers, upto 2000 MP3's & is supplied with a remote
- High quality Built-in echo with dedicated delay & feedback control on the Basic Cub U & Basic Cub S

Technical Specifications	Basic CUB	Basic CUB U	Basic CUB S
Nominal Gain (Mic/Line/Stereo Line)		65dB/55dB/0dB	
Max Gain (Mic/Line/Stereo Line)		83dB/73dB/18dB	
Input Levels Sensitivity			
Mic (Gain Min/Gain Max)		+4dBu / -65dBu	
Line (Gain Min /Gain Max)		+14dBu / -55dBu	
Input impedance			
Mic Input		Typically 5KΩ balanced	
Line input		20KΩ (Balanced) /10KΩ (Unbalanced)	
Stereo Line		20KΩ (Balanced) /10KΩ (Unbalanced)	
Main Output level (Nominal / Max)		0dBu (0.775V RMS) / +17dBu (5.5V RMS)	
Main Output Impedance		<50Ω	
Frequency Response		25Hz to 19KHz (+0/-1 dB)	
Total Harmonic Distortion		Better than 0.8%	
Signal to Noise Ratio		-76 dB	
Clip indication		4 dB prior to true clip	
Equalisation (Treble/Bass)		±16dB @ 10KHz/100 Hz	
EFX & USB	EFX	EFX & USB	-
Power Supply		150V~250V AC/50Hz	
Dimensions (W x D x H)mm		275 x 208 x 77	
Net Weight (Kg.)		1.5	