

DIVA P 363 3 channel LED Par Can (36 x 3W LED's)

The DIVA P 363, is a three channel LED Par can .This par can can operate in three different operating modes; DMX control, sound-active, or in a Master/Slave configuration.

Features:

- RGB Color Mixing.
- Color Strobe Effect.
- ED Chases Adjustable Speeds.
- Electronic Dimming 0-100%.
- Built in Microphone.
- DMX-512 protocol.
- DMX controller with Six DMX Modes. (Uses six DMX Channels).
- 3 Operating Modes - Sound Active, Master/Slave Mode.
- Digital Display for Address & Function Setting.



Technical Specifications:

MODEL	DIVA P 363
Light Source	36 pcs, 3W LEDs
Beam Angle	15°
Life Time	80,000-100,000 hours
Dimming	0-100% with regulated constant color control
Strobe	10 Flashed per second (any color)
Brightness	7900 Lux at 2 meter
Operation Mode	DMX 512, Manual, Sound, Internal program
DMX control	6 CH
Control panel	Digital 4 characters alphanumeric
Input voltage	AC100-240V, 50-60HZ
Max Power	120W
Maximum Ambient Temperature	40°C
Packing size (W x D x H) mm	255 x 255 x 365
Gross Weight (Kgs.)	3.5