


SEQ 312 Dual 31 Band Graphic Equalizer

The Studiomaster Professional SEQ 312 is an Ultra Musical Dual 31 Band Graphic Equalizer which meets the needs of the most demanding sound reinforcement environments, while offering the simplicity of straightforward controls.



Features:

- Professional Dual 31-Band stereo graphic equalizer with Constant Q factor
- Range setting switchable between +12 dB / -12dB to give a gradual variation as required
- LF Cut & Bypass Switches.
- Durable & Accurate 20mm Fader.
- LF Cut & Bypass Switches.
- Separate Sub out with selectable frequencies
- Balanced & Unbalanced I/O Connectors.



Technical Specifications:

MODELS	SEQ 312
Input Impedance	Balanced 20K Ω
Output Impedance	Balanced 600 Ω
Input Output Connectors	XLR & TRS
Frequency Response	20Hz-20 Khz
EQ Center Frequency	20Hz, 25Hz, 31.5Hz, 40Hz, 50Hz, 63Hz, 80Hz, 100Hz, 125Hz, 180Hz, 200Hz, 250Hz, 315Hz, 400Hz, 500Hz, 630Hz, 1KHz, 1.25KHz, 1.6KHz, 2KHz, 2.5KHz, 3.15KHz, 4 Khz, 5KHz, 6.3KHz, 8KHz, 10KHz, 12.5KHz, 16KHz, 20KHz.
EQ Cut / Boost	± 12 dB
Sub Woofer Frequency	63Hz - 315Hz
Low Cut	-3dB@63Hz
S/N Ratio	>90dB
THD	0.01%
Power Supply	230V AC / 50Hz
Dimensions (W x D x H)mm	482 x 145 x 88 (2U)
Net Weight (Kgs.)	2.9