

SFX - 8 Digital Effects Processor

The Studiomaster Professional SFX 8 is a high performance digital effects processor designed for Professional performers who require high-fidelity effects.



Features:

- Mic input (Balance) with GAIN control.
- Send/Return – It can be used as external effect processor with mixer using send/return.
- Delay and Reverb can be selected individually or combination of both giving more flexibility to user.
- PAN control.
- 6 led bargraph.
- Mono/Stereo Line input (Unbalance) with level control.
- Delay and Reverb with separate controls and selection.
- Wet/Dry signal mix control.
- Stereo unbalanced Master output with level control.
- Wide mains voltage operation 150VAC-240V.

Technical Specifications:

Model	SFX-8
Mono Mic Input Sensitivity	-56 dBu (±1dB) at Gain Control Max
Mono Mic Input Impedance	>3.0KΩ
Stereo Line Input Sensitivity	0dBu (±1dB)
Stereo Line Input Impedance	>27KΩ
Output Level	0dBu
Output Impedance	>40KΩ
Power supply	AC 150-250V 50Hz
Dimensions (W x D x H) mm	482 x 175 x 44 (1U)
Net Weight (Kgs.)	2.10

EFX Section - DELAY			EFX Section - REVERB	
Type	Time	Repeat	Type	Time
Echo	50ms to 1000ms	0-90%	Hall	2.0 - 10 Sec
Cross Feedback			Room	0.5 - 5.0 sec
3-Tap Pan			Plate	1.0 - 8.0 sc
One Shot Delay			Ambient	200ms - 200ms